

MP35U 35W-120W Mini USB/ Tuner/ Bluetooth Mixer Amplifier



Features

- Fashionable design, compact mini size public address amplifier;
- 3 MIC input (1 6.3mm MIC & 2 XLR MIC) , 1 EMC input, 2 lines input, 1 line output, Priority: EMC>MIC>Others.
- Tabletop amplifier with Mp3 player, FM radio & blue tooth
- Support both AC & DC 24V power supply.
- Ideal for classroom sound system use
- Rated power output at 35W, 60W
- Speaker output of 100V or 70V & 4Ohms-8 Ohms-16 Ohms
- Mp3 player with USB input on front panel, IR remote control for Mp3 player, FM radio and blue tooth
- LED indicators for power, clip, protect and signal
- Volume control for Mic 1-3, line 1-2, Mp3/FM, bass/treble and master
- With short-circuit, clip, overload and high temp protection

Specification

Model	MP35U/60U
Description	PA Amplifier with USB/SD & FM & Bluetooth
Rated power	35W/60W
Speaker Outputs	100V or 70V & 4Ohms-8 Ohms-16 Ohms
Connector	Mic1 input by unbalance 6.3mm phone jack MIC 2& MIC3 balance XLR socket Line1-2 inputs by RCA; Line output by RCA
Attenuation	Microphone1-3, line1-2 and Mp3/FM, bass/treble and master
MIC1 input sensitivity	5mV
MIC2 input sensitivity	5mV
MIC3 input sensitivity	5mV
AUX1 input sensitivity	300mV
AUX2 input sensitivity	300mV
EMC input sensitivity	300mV
MIC frequency response	80Hz~10kHz (±3dB)
AUX frequency response	70Hz~16kHz (±3dB)
Line Out	0.775(0dBV)
Noise	<5mV (4 ohm load output terminal)
THD	<1% 1KHz
Protection	Short-circuit, clip, overload and high temp protection
Treble adjustment	10dB (±2)
Bass adjustment	10dB (±2)
Power Supply	~110-240V & 24V DC /50-60Hz
Priority	EMC > MIC1 > others
Machine size(L×W×H)	290mm×219 mm×92.5 mm
Packing size	340mm×300mm×135mm (1PS)
Maximum packing size	610mm×350mm×280mm (4PS)
Net Weight	3.5Kg
Gross Weight	4.0Kg (1PS)